

**NAME**

minput\_save\_config – Save configurations in per–user customization file.

**SYNOPSIS**

int **minput\_save\_config** (void)

**DESCRIPTION**

Save configurations in per–user customization file. The **minput\_save\_config()** function saves the configurations done so far in the current session into the per–user customization file.

**RETURN VALUE**

If the operation was successful, 1 is returned. If the per–user customization file is currently locked, 0 is returned. In that case, the caller may wait for a while and try again. If the configuration file is not writable, –1 is returned. In that case, the caller may check the name of the file by calling **minput\_config\_file()**, make it writable if possible, and try again.

**SEE ALSO**

**minput\_config\_file()**

**COPYRIGHT**

Copyright (C) 2001 Information–technology Promotion Agency (IPA)

Copyright (C) 2001–2011 National Institute of Advanced Industrial Science and Technology (AIST)

Permission is granted to copy, distribute and/or modify this document under the terms of the GNU Free Documentation License <<http://www.gnu.org/licenses/fdl.html>>.

